

Reason Mixers controllers

MIDI Contr. #	Mixer 14:2	Line Mixer 6:2
0		
1		
2		
3		
4		
5		
6		
7	Master Level	Master Level
8	Channel 1 Level	Channel 1 Level
9	Channel 2 Level	Channel 2 Level
10	Channel 3 Level	Channel 3 Level
11		
12	Channel 4 Level	Channel 4 Level
13	Channel 5 Level	Channel 5 Level
14	Channel 6 Level	Channel 6 Level
15	Channel 7 Level	
16	Channel 8 Level	
17	Channel 9 Level	
18	Channel 10 Level	
19	Channel 11 Level	
20	Channel 12 Level	
21	Channel 13 Level	
22	Channel 14 Level	
23	Channel 1 Pan	Channel 1 Pan
24	Channel 2 Pan	Channel 2 Pan
25	Channel 3 Pan	Channel 3 Pan
26	Channel 4 Pan	Channel 4 Pan
27	Channel 5 Pan	Channel 5 Pan
28	Channel 6 Pan	Channel 6 Pan
29	Channel 7 Pan	
30	Channel 8 Pan	
31	Channel 9 Pan	
32		
33	Channel 10 Pan	
34	Channel 11 Pan	
35	Channel 12 Pan	
36	Channel 13 Pan	
37	Channel 14 Pan	
38		
39	Channel 1 Aux 1 Send	Channel 1 Aux Send
40	Channel 2 Aux 1 Send	Channel 2 Aux Send
41	Channel 3 Aux 1 Send	Channel 3 Aux Send
42	Channel 4 Aux 1 Send	Channel 4 Aux Send
43	Channel 5 Aux 1 Send	Channel 5 Aux Send
44	Channel 6 Aux 1 Send	Channel 6 Aux Send
45	Channel 7 Aux 1 Send	
46	Channel 8 Aux 1 Send	
47	Channel 9 Aux 1 Send	
48	Channel 10 Aux 1 Send	
49	Channel 11 Aux 1 Send	
50	Channel 12 Aux 1 Send	
51	Channel 13 Aux 1 Send	
52	Channel 14 Aux 1 Send	
53	Channel 1 Aux 2 Send	
54	Channel 2 Aux 2 Send	
55	Channel 3 Aux 2 Send	
56	Channel 4 Aux 2 Send	
57	Channel 5 Aux 2 Send	
58	Channel 6 Aux 2 Send	
59	Channel 7 Aux 2 Send	
60	Channel 8 Aux 2 Send	
61	Channel 9 Aux 2 Send	
62	Channel 10 Aux 2 Send	
63	Channel 11 Aux 2 Send	
64		
65	Channel 12 Aux 2 Send	
66	Channel 13 Aux 2 Send	
67	Channel 14 Aux 2 Send	
68	Channel 1 Bass Amount	
69	Channel 2 Bass Amount	
70	Channel 3 Bass Amount	

MIDI Contr. #	Mixer 14:2
71	Channel 4 Bass Amount
72	Channel 5 Bass Amount
73	Channel 6 Bass Amount
74	Channel 7 Bass Amount
75	Channel 8 Bass Amount
76	Channel 9 Bass Amount
77	Channel 10 Bass Amount
78	Channel 11 Bass Amount
79	Channel 12 Bass Amount
80	Channel 13 Bass Amount
81	Channel 14 Bass Amount
82	Channel 1 Treble Amount
83	Channel 2 Treble Amount
84	Channel 3 Treble Amount
85	Channel 4 Treble Amount
86	Channel 5 Treble Amount
87	Channel 6 Treble Amount
88	Channel 7 Treble Amount
89	Channel 8 Treble Amount
90	Channel 9 Treble Amount
91	Channel 10 Treble Amount
92	Channel 11 Treble Amount
93	Channel 12 Treble Amount
94	Channel 13 Treble Amount
95	Channel 14 Treble Amount
96	
97	
98	
99	
100	
101	
102	Channel 1 Aux 3 Send
103	Channel 2 Aux 3 Send
104	Channel 3 Aux 3 Send
105	Channel 4 Aux 3 Send
106	Channel 5 Aux 3 Send
107	Channel 6 Aux 3 Send
108	Channel 7 Aux 3 Send
109	Channel 8 Aux 3 Send
110	Channel 9 Aux 3 Send
111	Channel 10 Aux 3 Send
112	Channel 11 Aux 3 Send
113	Channel 12 Aux 3 Send
114	Channel 13 Aux 3 Send
115	Channel 14 Aux 3 Send
116	Aux 1 Return Level
117	Aux 2 Return Level
118	Aux 3 Return Level
119	Aux 4 Return Level
120	
121	
122	
123	
124	
125	
126	
127	